

How to select the correct motherboard for the SlimLine with an Aspen motherboard Model PAS*

There are two versions of this mainboard and the speed of the processor determines which board should be ordered.

There are two ways to find this information.

Option 1

Look up the serial number in the Solectron BOM in the knowledge base

It won't list a mainboard, but it will list the CPU part and the speed will be listed in the description.

Option 2

Get the entire model number. All models will start with PAS and the fourth character will tell the CPU speed.

Character	P (Powermate)	A (Aspen)	S (slimline)	See below		
Meaning	Series	Family	Form Factor	CPU		
Order	1st	2nd	3rd	4th		
	P	A	S	0=	500Celeron	Order the 600-R
	P	A	S	1=	533Celeron	Order the 600-R
	P	A	S	2=	566 Celeron	Order the 600-R
	P	A	S	3=	600 Celeron	Order the 600-R
	P	A	S	4=	633 Celeron	Order the 600-R
	P	A	S	5=	677 Celeron	Order the 600-R
	P	A	S	6=	700 Celeron	Order the 600-R
	P	A	S	7=	733Celeron	Order the 600-R
	P	A	S	8=	800Celeron	Order the 600-R
	P	A	S	9=		
	P	A	S	A=	PIII600/133	Order the 600-R
	P	A	S	B=	PIII667/133	Order the 600-R
	P	A	S	C=	PIII733/133	Order the 600-R
	P	A	S	D=	PIII800/133	Order the 600-R
	P	A	S	E=	PIII866/133	Order the 600-R
	P	A	S	F=	PIII933/133	Order the 700-R
	P	A	S	G=	PIII1GHz/133	Order the 700-R

If the processor speed is 866mhz or lower, order 6777910600-R.

If the processor speed is 933mhz or 1 GHz, order 6777910700-R.

Date : January 24, 2003